

Ei414



RadioLINK+ Fire/CO Alarm Interface



- Connects Aico domestic alarms to external devices, such as Fire Panel systems, Telecare/Warden Call and Sprinkler systems
- Mains powered with Rechargeable Lithium Back-up
- RadioLINK+ Wireless interconnection
- Key Switch to control on, off and test status
- 5 year guarantee



Description

The Ei414 RadioLINK Fire/CO Alarm Interface connects Aico fire and CO alarms with a range of external devices. The module will receive 'Fire', 'CO' and 'Service' signals from RadioLINK devices and switch the relevant built-in relay

Technical

| | | | |
|------------------------------|--|---------------------------|----------------------|
| RF Frequency (MHz) | 868.499 | RF Range (m) | >100 in free air |
| Indicators | Green - Power / Red - CO, Fire or Service / Blue - RF transmission | Supply Voltage (V) | 230/10-30 |
| Voltage Type | AC/DC | Battery Type | Lithium rechargeable |
| Power Consumption (W) | 1.6(AC) / 1.8(DC) | Technologies | RadioLINK+ |

Dimensions & Weights

| | | | |
|-----------------------------|-------|----------------------------|------|
| Depth (mm) | 50 | Height (mm) | 100 |
| Width (mm) | 220 | Product weight (kg) | 0.39 |
| Packaged weight (kg) | 0.438 | | |

Approvals & Warranty

| | | | |
|-----------------|-----------------|-------------------|---------------|
| Warranty | 5 year warranty | EAN Number | 5099383005066 |
|-----------------|-----------------|-------------------|---------------|

Environmental

| | | | |
|---------------------------|-------|-------------------------------|-----------|
| Humidity Range (%) | 15-95 | Temperature Range (°C) | -10 to 40 |
|---------------------------|-------|-------------------------------|-----------|